Prosperity Dielectrics Co., Ltd.

No.566-1, Kaoshi Rd., Yangmei, Taoyuan 32668, Taiwan (R.O.C.) Tel: 886-3-4753355 Fax: 886-3-4854959

Messrs.	:	一般共用

Date : 2019/11/11

APPROVAL SHEET

Product Name: Stacked Capacitors

Part No. : FE Series

Description: Size 1210~2225, C0G/X7R, 50~1000Vdc

PREPARED BY	APPROVED BY
ERITY DIFFERENCE	1000,10, All

信昌電子陶瓷股份有限公司

PROSPERITY DIELECTRICS CO., LTD.

桃園市楊梅區高獅路 566-1 號 http://www.pdc.com.tw

Tel: 03-4753355 ext: Fax: 03-4854959

Contactor : _____ Mobile : _____

Prosperity Dielectrics Co., Ltd.

No.566-1, Kaoshi Rd., Yangmei, Taoyuan 32668, Taiwan (R.O.C.) Tel: 886-3-4753355 Fax: 886-3-4854959

SPECIFICATION

FOR

Product Name: Stacked Capacitors

Part No.: FE Series

Description: Size 1210~2225, C0G/X7R, 50~1000Vdc

SPEC. No.: FE-000-001-08

DATE: 2019/11/11

DRAWN BY	CHECEKED BY	APPROVED BY
Jane Hsiao	Yvens Chou	Joseph Ling

Prosperity Dielectrics Co., Ltd.

1. INTRODUCTION

FE Series green type capacitors are manufactured by using green materials without lead and cadmium. These capacitors to achieve a unique structure of high reliability. The use of metal lead frame, can absorb the heat and mechanical stress. ESR (equivalent series resistance), ESL (equivalent series inductance) is small, the most suitable for high frequency operation of the rectifier power supply.

2. FEATURES

- a. High reliability and stability.
- b. Higher mechanical endurance.
- c. Anti thermal stress and mechanical stress.
- d. Improved vibration performance.
- e. More capacitance without changing footprint.
- f. RoHS Compliant.

3. APPLICATIONS

- a. DC to DC converter.
- b. High voltage coupling/DC blocking.
- c. Back-lighting inverters.
- d. Snubbers in high frequency power converters.
- e. Power supplies.
- f. Surge protection.
- g. Filtering, smoothing, and decoupling application.

4. HOW TO ORDER

<u>FE</u>	<u>2H</u>	<u>X</u>	<u>106</u>	<u>K</u>	<u>500</u>	L	<u>G</u>	<u>K</u>	<u>M</u>
PDC Family	Size	Dielectric	Capacitance	Tolerance	Rated Voltage	Packaging	Thickness	Control Code	Secial Code
Table 1	Table 2	Table 3	Table 4	Table 5	Table 6	Table 7	Table 8	Table 9	Table 10

Table 1	PDC Family		
Code	Description	PASSIVE	U
FE	Stacked Capacitors Series		
		0	

Tab	le 2	Stack chip quantity and chip size					
The first digit : # of chips in stack							
Second digit code : chip size (below)					SAITVO:		
Code	Des	scription	Code	Description	Code	Description	
Α	1210	(3225)	G	1825 (4563)	I	2225 (5763)	
С	1812	2 (4532)	Н	2220 (5750)			

<u> </u>					· ·	
Table 3 Dielectric Material Characteristics						
Code		Description		Code	С	Description
N		C0G		Х		X7R

Table	4	Сара	acitance	Rule Code
Code		Description	Code	Description
R47	0.47pF		102	102=10x10 ² =1000pF
0R5	0.5pF		104	104=10x10 ⁴ =100nF
100	10	00=10x10 ⁰ =10pF	106	106=10x10 ⁶ =10µF

Table	e 5	Tolerance				
Code	Description	Code	Description	Code	Description	
Α	±0.05 pF		-10% ~ 0%	Q	±0.03 pF	
В	±0.10 pF	J	±5 %	Z	-20% ~ +80%	
С	±0.25 pF	K	±10 %	Х	+10% ~ +20%	
D	±0.50 pF	L	0% ~ +10%			
F	±1 %	М	±20 %			
G	±2 %	N	-5% ~ +10%			
Н	±3 %	Р	±0.02 pF			

Specification No.: FE-000-001-08

Table	6	Rated Voltage				
Code	o⊂∈ Des	cription	Code	Description	Code	Description
250	25	Vdc	201	200Vdc	501	500Vdc
500	50	Vdc	251	250Vdc	631	630Vdc
101	10	0Vdc	401	400Vdc	102	1000Vdc

activ			
Table	7 Pack	aging Typ	е
Code	Description	Code	Description
В	Bulk	Т	Tray package
L	Tape and 13" Reel, Embossed Tape		

Т	able 8		Thickness	Descrip	otion
Code	Description	Code	Description	Code	Description
Α	3.00±0.35 mm	J	7.80±0.35 mm	S	12.60±0.35 mm
В	3.60±0.35 mm	K	8.40±0.35 mm	Т	13.20±0.35 mm
С	4.20±0.35 mm	L	9.00±0.35 mm	U	1.70±0.25 mm
D	4.80±0.35 mm	М	9.60±0.35 mm	V	2.10±0.25 mm
Е	5.40±0.35 mm	Ν	10.20±0.35 mm	W	2.50±0.25 mm
F	6.00±0.35 mm	Р	10.80±0.35 mm		
G	6.60±0.35 mm	Q	11.40±0.35 mm		
Н	7.20±0.35 mm	R	12.00±0.35 mm		

Table 9	Special Control Code						
Code	Description	Code	Description				
L	L type lea	K	K type lead				
J	J type lead	В	B type lead				
S	Straight type lead	F	Straight type lead				

Table 10	Special Control Code					
М	Automotive					

Prosperity Dielectrics Co., Ltd.

5. EXTERNAL DIMENSIONS

Size Inch (mm)	L (mm)	W (mm)	Code / T (mm)	E (mm)	w L
1210 (3225)	3.50±0.40	2.50±0.40		1.70±0.15	L Type Lead
1812 (4532)	4.80±0.40	3.20±0.40		1.70±0.15	₩, / *
1825 (4563)	4.80±0.40	6.30±0.50	Reference Table 8	1.70±0.15	1
2220 (5750)	6.00±0.50	5.00±0.50		1.70±0.15	J Type Lead ⊢ E →
2225 (5763)	6.00±0.50	6.30±0.50		1.70±0.15	Fig. 5.1 The outline of Stacked Capacitors

6. GENERAL ELECTRICAL DATA

Dielectric	COG 新有 信息	X7R			
Size	1210, 1812, 1825, 2220, 2225	1210, 1812, 1825, 2220, 2225			
Rated voltage (WVDC)	50V, 100V, 200V, 250V, 500V, 630V, 1000V	50V, 100V, 200V, 250V, 500V, 630V, 1000V			
Capacitance range	400nF Max.	66μF Max.			
Capacitance tolerance	Reference to Table 5 YSTEM ALLIANCE	Reference to Table 5			
Tan δ	Cap. Range Q Spec. Cap. Q≥400+20C Cap.≥30pF Q≥1000	Cap. Range D.F. Spec. 1210≥3.3μF ≤5.0% 1812~2225≥10μF ≤5.0% Other ≤2.5%			
	Measured at the condition of 30~70% related humidity For 25°C at ambient temperature Cap. Range Test Condition Cap.<1000pF 1.0±0.2Vrms, 1.0MHz±10% Cap.≥1000pF 1.0±0.2Vrms, 1.0KHz±10%	Measured at the condition of 30~70% related humidity Preconditioning for Class II MLCC : Perform a heat treatment at 150±10°C for 1 hour, then leave in ambient condition (25°C) for 24±2 hours before measurement Cap. Range Test Condition Cap.≤10μF 1.0±0.2Vrms, 1.0KHz±10% Cap.>10μpF 0.5±0.2Vrms, 120Hz±20%			
Insulation resistance at Ur	≥10GΩ or RxC≥500Ω-F, whichever is smaller	≥10GΩ or RxC≥100Ω-F, whichever is smaller			
Operating temperature	-55 to +125°C	-55 to +125°C			
Capacitance characteristic	±30ppm / °C	±15%			
Termination	L / J / Straight type lead	L / J / Straight type lead			

Specification No. : FE-000-001-08 ~ 2 ~

Prosperity Dielectrics Co., Ltd.

7. CAPACITANCE RANGE (Max.)

7-1. C0G

Dimension	Code			Ra	ated Volta	ge		
Dimension	Code	50V	100V	200V	250V	500V	630V	1000V
1210	1A	393	223	103	103	103	103	222
	1C	104	473	273	273	223	223	392
1812	2C	224(M)	104	563	563	473(M)	473(M)	822
	3C	304	144	813	813	663	663	123
	1G	104	104	683	683	473	223	103
1825	2G	224(M)	224(M)	134	134	104	473(M)	223(M)
1025	3G	304	304	204	204	144	663	303
	4G	334(M)	-	-	-	194	883	-
	1H	104	104	683	683	473	223	103
2220	2H	224(M)	224(M)	134	134	104	473(M)	223(M)
2220	3H	304	304	204	204	144	663	303
	4H	334	-	-	-	164	883	-
	11	104	104	104	104	823	683	103
2225	21	224(M)	224(M)	224(M)	224(M)	184(M)	134	223(M)
2225	31	304	304	304	304	254	204	303
	41	404	334	-	-	-	-	333

7-2. X7R

Dimension	Code			Ra	ated Volta	ge		
Difficusion	Code	50V	100V	200V	250V	500V	630V	1000V
1210	1A	475	335	684	684	104	104	473
	1C	106	475	105	105	474	224	104
1812	2C	226(M)	106	225(M)	225(M)	105	474(M)	224(M)
	3C	306	146	305	305	145	664	304
	1G	106	106	105	105	564	564	104
1825	2G	226(M)	226(M)	225(M)	225(M)	125(M)	125(M)	224(M)
1025	3G	306	306	305	305	175	175	304
	4G	-	-	405	405	195	195	334
	1H	226	106	225	225	474	474	224
2220	2H	476(M)	226(M)	475(M)	475(M)	105	105	474(M)
2220	3H	666	306	665	665	145	145	664
	4H	-	-	-	-	195	195	-
	11	106	106	275	275	564	564	224
2225	21	226(M)	226(M)	565	565	125(M)	125(M)	474(M)
2225	31	306	306	815	815	175	175	664
	41	-	-	-	-	235	235	-

7-3. Customizable, Please contact the liaison.

Specification No.: FE-000-001-08 ~ 3 ~

Prosperity Dielectrics Co., Ltd.

8. RELIABILITY TEST CONDITIONS AND REQUIREMENTS

No.	Item			Test Condition				Requirements		
	Visual and				* No remarkable defect.					
1.	Dimensions					* Dimensions to confirm to individual specification sheet.				
2.	Capacitance	* Class I :				* Shall not exceed the limits given in the detailed spec.				
		Cap.≤1000pF, 1.0±0.2Vrms, 1MHz±10%.			Dielectric	Cap. Range	Q/D.F.			
	Q/D.F.	Cap.>1000pF, 1.0±0.2Vrms, 1KHz±10%.			Class I (C0G)	Cap.≥30pF	Q≥1000			
3.	(Dissipation	* Class II :					Class I (COG)	Cap.<30pF	Q≥400+20C	
	Factor)	Cap.≤10µ	F, 1.0±0	0.2Vrms, 1KHz±1	0%.		Class II (X7R)	1210≥3.3µF & 1812~2225≥10µF	D.F.≤5.0%	
		Cap.>10µ	ıF, 0.5±0).2Vrms, 120Hz±2	20%.		,	Other	D.F.≤2.5%	
		* With no e	lectrical	load						
	Temperature	T.C.		Operating T	emp.		T.C.	Capacitance Chan		
4.	Coefficient	C0G		-55∼125°C a	t 25°C		COG	Within ±30ppm/°C	<u> </u>	
		X7R		-55∼125°C a	t 25°C		X7R	Within ±15%		
					AN ETT	3	1夏第			
		Rated Vo		Apply Voltage	Test Time	- IV	Dielectric	Requirements		
5.	Insulation	≤100		1 times of U _R	Max. 120 s	ec.	Class I	≥10GΩ or RxC≥500Ω-F, which	ever is smaller	
	Resistance	100 <v≤< td=""><td></td><td>1 times of U_R</td><td>60 sec.</td><td></td><td>Class II</td><td>≥10GΩ or RxC≥100Ω-F, which</td><td>ever is smaller</td></v≤<>		1 times of U _R	60 sec.		Class II	≥10GΩ or RxC≥100Ω-F, which	ever is smaller	
		>500	,	500VdC	60 sec.	1				
		Rated	Voltage	Co	ondition		M ALLIANCE	8		
	6. Dielectric	≤100 2.5 times of U _R		A ALLIANCE DE S						
		100 <v≤250 2.0="" of="" times="" u<sub="">R</v≤250>								
6.		250 <v≤500 1.5="" of="" times="" u<sub="">R</v≤500>			* No evidence of damage or flash over during test.					
		≥630 1.2 times of U _R				ie l	ctrics			
		* Duration : 1 to 5 sec. * Charge and discharge current less than 50mA, TDIC			co [70.					
		Criarye a	ilu uiscii	arge current less	than some.	- IKI	2001	(01)		
		* Conduct t	he 100	cycles according	to the					
		temperatu	ires and	time.						
		Step		Temp.(°C)	Time(m		* No remarkable	damage.		
				rating temp. +0/-			* Cap. change :	50/ an 10 05a5 which aven is larger		
_	Temperature		Room te	rinp. erating temp. +3/-	2~3 ·0 30±3		X7R Within ±2.	5% or ±0.25pF, whichever is larger. 5%.		
7.	Cycle		Room te		2~3		* Q/D.F. :			
				surement (Class		pply	COG : Q≥100% of initial requirement.			
		de-aging at 150°C for 1hr then set for 24±2 hrs at			X7R: D.F.≤150% of initial requirement. * I.R.: To meet the initial requirement. p.					
		room temp. * Measurement to be made after keeping at room temp. for 24±2 hrs (Class I) or 48±4 hrs (Class II).								
		* Test temp					* No remarkable damage.			
		* Humidity * Test time					* Cap. change :	0% or ±0.5pF, whichever is larger.		
0	Humidity			surement (Class	II only) : To a	ply	X7R Within ±12			
8.	(Damp Heat) Steady State	de-aging	at 150°0	of for 1hr then set			* Q/D.F. :			
	y o.u.o	room tem	•	oo mada aftar kas	ning at room	tomn	C0G : Q≥350.	% of initial requirement		
				oe made after kee ss I) or 48±4 hrs (-	еттр	X7R : D.F.≤200% of initial requirement.* I.R. : ≥1GΩ or RxC≥50Ω-F, whichever is smaller.			
			, , , , ,	,	,					

Specification No.: FE-000-001-08

~ 4 ~

Prosperity Dielectrics Co., Ltd.

8. RELIABILITY TEST CONDITIONS AND REQUIREMENTS

No.	Item		st Condition	Requirements
9.	Humidity (Damp Heat) Load	* Test temp. : 40±2°C. * Humidity : 90~95%R * Test time : 500 +24/- * To apply voltage : Ra * Before initial measur de-aging at 150°C fo room temp. * Measurement to be r	:H.	* No remarkable damage. * Cap. change: C0G Within ±7.5% or ±0.75pF, whichever is larger. X7R Within ±12.5%. * Q/D.F.: C0G: Q≥200. X7R: D.F.≤200% of initial requirement. * I.R.: ≥500MΩ or RxC≥25Ω-F, whichever is smaller.
10.	High Temperature Load (Endurance)	COG/X7R = 200s COG/X7R = = = * Exception items (X7F (1) 150% of rated volvents (1) 150% of rated volvents (1) 150% of rated volvents (1) 1825 (1)	d Vol.(V) Apply Voltage 2.0 times of U _R 630 1.5 times of U _R 1000 1.0 times of U _R R only): tage for below range: Cap.≥106 Cap.≥124 Cap.≥124 Cap.≥15µF tage for below range: Rated Voltage Capacitance ≥100V Cap.≥3.3µF	* No remarkable damage. * Cap, change: CGP, within ±3.0% or ±0.3pF, whichever is larger. X7R Within ±12.5%. * Q/D.F.: CGC: Q≥350. X7R: D.F.≤200% of initial requirement. * I.R.: ≥1GΩ or RxC≥50Ω-F, whichever is smaller.

Specification No. : FE-000-001-08 ~ 5 ~

Prosperity Dielectrics Co., Ltd.

8. RELIABILITY TEST CONDITIONS AND REQUIREMENTS

No.	Item	Test Condition	Requirements
11.	Adhesive Strength of Termination	* Capacitors mounted on a substrate. A force of 10N applied perpendicular to the place of substrate and parallel the line joining the center of terminations for 10±1 second. Pressurizing force Capacitor P.C. Board	* No remarkable damage or removal of the terminations.
14.	Bending Test	* The middle part of substrate shall be pressurized by means of the pressurizing rod at a rate of about 1mm per second until the deflection becomes 5mm. R = 230 Unit : mm	This capacitance change means the change of capacitance under specified flexure of substrate from the capacitance measured before the test)
15.	Vibration Resistance	* Vibration frequency: 10~55 Hz/min. * Total amplitude: 1.5mm. * Test time: 6 hrs. (Two hrs each in three mutually perpendicular directions) * Before initial measurement (Class II only): To apply de-aging at 150°C for 1hr then set for 24±2 hrs at room temp. * Measurement to be made after keeping at room temp. for 24±2 hrs (Class I) or 48±4 hrs (Class II).	* No remarkable damage. * Cap. change and D.F. : To meet initial spec.

Specification No. : FE-000-001-08 ~ 6 ~

Prosperity Dielectrics Co., Ltd.

9. APPLICATION NOTES

STORAGE

To prevent the damage of solderability of terminations, the following storage conditions are recommended: Indoors under 5 ~ 40°C and 20% ~ 70% RH.

No harmful gases containing sulfuric acid, ammonia, hydrogen sulfide or chlorine.

Packaging should not be opened until the capacitors are required for use. If opened, the pack should be re-sealed as soon as is practicable. Taped product should be stored out of direct sunlight, which might promote deterioration in tape or adhesion performance. The product is recommended to be used within 12 months after shipment and checked the solderability before use.

HANDLING

Chip capacitors are dense, hard, brittle, and abrasive materials. They are liable to suffer mechanical damage, in the form of cracks or chips. Chip Capacitors should be handled with care to avoid contamination or damage. To use vacuum or plastic tweezers to pick up or plastic tweezers is recommended for manual placement. Tape and reeled packages are suitable for automatic pick and placement machine.


PREHEAT

In order to minimize the risk of thermal shock during soldering, a carefully controlled preheat is required. The rate of preheat should not exceed 3°C per second.

SOLDERING

Use middy activated rosin RA and RMA fluxes do not use activated flux. The amount of solder in each solder joint should be controlled to prevent the damage of chip capacitors caused by the stress between solder, chips, and substrate.

a.) Reflow soldering:



COOLING

After soldering, cool the chips and the substrate gradually to room temperature. Natural cooling in air is recommended to minimize stress in the solder joint.

CLEANING

All flux residues must be removed by using suitable electronic-grade vapor-cleaning solvents to eliminate contamination that could cause electrolytic surface corrosion. Good results can be obtained by using ultrasonic cleaning of the solvent. The choice of the proper system is depends upon many factors such as component mix. flux, and solder paste and assembly method. The ability of the cleaning system to remove flux residues and contamination from under the chips is very important.

Specification No.: FE-000-001-08 ~ 7 ~